

PHYS 273, Fall 2017, Homework 3

Due date: Thursday, **October 26th, 2017**

1. *Capacity of the carrier pigeon channel.* Consider a commander of an army besieged in a fort for whom the only means of communication to his allies is a set of carrier pigeons. Assume that each carrier pigeon can carry one letter (8 bits), that pigeons are released once every 5 minutes, and that each pigeon takes exactly 3 minutes to reach its destination.

- a. Assuming that all the pigeons reach safely, what is the capacity of this link in bits/hour?
- b. Now assume that the enemies try to shoot down the pigeons and that they manage to hit a fraction α of them. Since the pigeons are sent at a constant rate, the receiver knows when the pigeons are missing. What is the capacity of this link?
- c. Now assume that the enemy is more cunning and that every time they shoot down a pigeon, they send out a dummy pigeon carrying a random letter (chosen uniformly from all 8-bit letters). What is the capacity of this link in bits/hour?

Set up an appropriate model for the channel in each of the above cases, and indicate how to go about finding the capacity.

2. *Information and motor control.* An important task in motor control is tracking. When objects move smoothly across our visual field, we track their motion by moving our eyes, which is called smooth pursuit.

- a. The simplest version of the tracking problem is that we have an observable x , which is generated according to a probability distribution $P(x)$ and we try to generate a variable y that is as close as possible to x , in the sense of the mean-square error $\epsilon = \langle (y - x)^2 \rangle$. Develop a variational principle for the choice of $P(y|x)$, in which you aim to find the minimum amount of mutual information $I(x, y)$ needed to reach a certain value of ϵ . (**Hint:** You may try the method of Lagrange multipliers. Ensure that all constraints (a continuum of them) are taken into account.)
- b. Solve the problem formulated in (a), i.e. find an expression for $P(y|x)$ and derive the corresponding consistency conditions.
- c. Assume that $P(x)$ is Gaussian. Solve the consistency conditions and plot the rate distortion curve $I(x, y)$ vs ϵ .